

Токовые клещи

DT-361/363/366, DT-380/381/382/383, DT-371/371B/371BL/372/373/375/375BT

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: mce@nt-rt.ru || сайт: <https://cem.nt-rt.ru/>

DT-361/363/366



Compact AC,AC/DC Autoranging Clamp Meters

The 360 series clamp meters offer all needed features for measurement. It with small bodies and jaws design for perfectly handhold and tight place testing. A large backlit display (on most models) is easy to see and a handy Display Hold keeps measurements on the display. Measuring starting current for motors, lighting, etc. is easy with the inrush current function (366 only).

- Double molded plastic housing
- Inrush current function (366 only)
- Auto Power Off

Features	DT-360	DT-361	DT-362	DT-363	DT-366
Current measurement	AC	AC	AC/DC	AC/DC	AC/DC
Max. Resolution	1mA	1mA	10mA	10mA	10mA
LCD display counts	2000	4000	4000	4000	6000
AC True RMS				*	*
Display with backlight	*	*	*	*	*
Data Hold	*	*	*	*	*
Max Hold	*				
Zero Function			*	*	*
Auto Power Off	*	*	*	*	*
Low battery indication	*	*	*	*	*
Peak Current				*	
Inrush Current					*
1.2" (30mm) Jaw opening	*	*	*	*	*

Size (H x W x D): 197mm x 70mm x 40mm

Weight: 183g

Specifications							
Function	Max Range	Basic Accuracy	DT-360	DT-361	DT-362	DT-363	DT-363
Voltage DC	600V	$\pm(0.5\%+1d)$	*	*	*	*	*
Voltage AC	600V	$\pm(1.5\%+2d)$	*	*	*	*	*
Current DC	400A	$\pm(2.0\%+5d)$			*	*	600A
Current AC	400A	$\pm(2.5\%+4d)$	*	*	*	*	*
Resistance	40M Ω	$\pm(3.0\%+5d)$	20M Ω	*	*	*	60M Ω
Temperature	1000°C/ 1832°F	$\pm(3.0\%+3d)$		*	*	*	*
Capacitance	100uF	$\pm(2.5\%+5d)$			*	40mF	60mF
Frequency	10MHz	$\pm(1.2\%+2d)$			*	*	*
Inrush Current	600A	$\pm(1.5\%+2d)$					*
Continuity check	Buzzer sounds at 50 Ω		*	*	*	*	*
Diode test	Test current 0.3mA		*	*	*	*	*

DT-380/381/382/383 Compact AC, AC/DC Autoranging Clamp Meters

The 380 series clamp meters offer all the features you need to fit the way you work. The small bodies and jaws fit perfectly in your hand and into tight places.

Features				
	380	381	382	383
Current measurement	AC	AC	AC/DC	AC/DC
LCD display counts	2000	4000	2000	4000
Data Hold	*	*	*	*
REL (Zero) Function			*	*
Auto Power Off	*	*	*	*
Low battery indication	*	*	*	*
1.2" (30mm) Jaw opening	*	*	*	*
NCV Detection	*	*	*	*
Flashlight	*	*	*	*

Specifications						
Function	Max Range	Basic Accuracy	380	381	382	383
Voltage DC	600V	$\pm(0.5\%+1d)$	*	*	*	*
Voltage AC	600V	$\pm(1.5\%+2d)$	*	*	*	*
Current DC	400A	$\pm(2.0\%+5d)$			200A	*
Current AC	400A	$\pm(2.5\%+4d)$	*	*	200A	*
Resistance	40M Ω	$\pm(3.0\%+5d)$	20M Ω	*	20M Ω	*
Temperature	1000°C/ 1832°F	$\pm(3.0\%+3d)$	*	*	*	*
Capacitance	100uF	$\pm(2.5\%+5d)$		*		*
Frequency	10MHz	$\pm(1.2\%+2d)$		10kHz		10kHz
Continuity check	Buzzer sounds at 50 Ω					
Diode test	Test current 0.3mA					

Size(HxWxD): 230mm x 82mm x 40mm
Weight: 230g

Accessories:

Test leads, gift box with carrying case, temperature probe and Two“AAA”1.5V batteries.



EMC & LVD
 EN: 61326
 EN: 61010-1
 EN: 61010-02-032
 EN: 61010-02-033



Model 383

DT-371/371B/371BL/372/373/375/375BT

Compact AC, AC/DC Autoranging Clamp Meters

CEM

The 371 series clamp meters offer all needed features for measurement. It is with small bodies and jaws design for perfect handhold and tight place testing. A large backlit display (on most models) is easy to see and a handy Display Hold keeps measurements on the display.

- Double molded plastic housing
- Auto Power Off



EMC & LVD
EN: 61326
EN: 61010-1
EN: 61010-02-032
EN: 61010-02-033



True RMS (375/375BT)

1.2" (30mm) Jaw opening

Features

	371	371B	371BL	372	373	375	375BT
Current measurement	AC	AC	AC	AC	AC/DC	AC/DC	AC/DC
Max. Resolution	1mA	1mA	1mA	1mA	10mA	10mA	10mA
LCD display counts	2000	2000	2000	4000	4000	4000	6000
AC True RMS	*					*	*
Display with backlight	*	*	*	*	*	*	*
Data Hold	*	*	*	*	*	*	*
Max Hold	*					*	*
Zero Function					*	*	*
Auto Power Off	*	*	*	*	*	*	*
Low battery indication	*	*	*	*	*	*	*
Bluetooth							*
1.2" (30mm) Jaw opening	*	*	*	*	*	*	*

Specifications

Function	Max Range	Basic Accuracy	371	371B	371BL	372	373	375	375BT
Voltage DC	600V	±(0.5%+1d)	*	*	*	*	*	*	*
Voltage AC	600V	±(1.5%+2d)	*	*	*	*	*	*	*
Current DC	400A	±(2.0%+5d)					*	*	*
Current AC	400A	±(2.5%+4d)	*	*	*	*	*	*	*
Flexible A	3000A	±(3.0%+5d)							*
Resistance	40MΩ	±(3.0%+5d)	20MΩ	20MΩ	20MΩ	*	*	*	60MΩ
Temperature	1000°C/1832°F	±(3.0%+3d)		*				*	*
Capacitance	100uF	±(2.5%+5d)					*	4000μF	6000μF
Frequency	10MHz	±(1.2%+2d)				*	*	*	*
Continuity check	Buzzer sounds at 50Ω		*	*	*	30Ω	30Ω	*	*
Diode test	Test current 0.3mA		*	*	*	*	*	*	*

Size(HxWxD): 197mm x 70mm x 40mm

Weight: 183g

Accessories: Test leads, gift box with carrying case, temperature probe(371B, 375, 375BT, 376 only), 1.5Vx2 "AAA" batteries.



Model 371



Model 373



Model 375BT





По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: mce@nt-rt.ru || сайт: <https://cem.nt-rt.ru/>