

Цифровые мультиметры DT-3216, DT-3218, DT-3219, DT-3280, DT-3280B, DT-991, DT-9932FC

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: mce@nt-rt.ru || сайт: <https://cem.nt-rt.ru/>

- 7 functions Pen-type Digital Multimeters
- Large 3-3/4 digital LCD display with Bargraph
- Full function indication
- Diode and audible continuity



Model 3280B



Model 3218

Specifications

Function	Max range	Basic accuracy	3216	3218	3219	3260	3280	3280B	3290
Voltage DC	600V	±0.8%	*	*	*	*	*	*	*
Voltage AC	600V	±1.2%	*	*	*	*	*	*	*
Current DC		±1.5%		340mA	400mA	400mA	200mA		400mA
Current AC		±2.0%		340mA	400mA	400mA	200mA		400mA
Resistance	40MΩ	±3.0%	20MΩ	30MΩ	*	±1.0%	20MΩ	20MΩ	*
Capacitance	40mF	±3.5%				*			
Non-contact voltage: 50-600V					*		*	*	
Continuity: <35Ω									
Diode test: Test voltage max. 3.4V									

Size(HxWxD): 220mm x 40mm x 33mm

Weight: 215g

Accessories: Clamshell and button battery



EMC & LVD

EN: 61326

EN: 61010-1

EN: 61010-02-032

EN: 61010-02-033



DT-991 Series & 200 Series/9932FC High Performance Digital Multimeters



Model 204



Model 991



Specifications

Function	Max Range	Basic Accuracy	991/200	992/201	993/202	202T	204
Voltage DC	600V	±(0.8%±2d)	*	*	*	*	*
Voltage AC	600V	±(1.2%±10d)	*	*	*	*	*
Current DC	10A	±(1.2%±2d)	*	*	*	*	*
Current AC	10A	±(1.8%±7d)		*/-	*	*	*
Resistance	2000Ω	±(0.8%±2d)	*	*	20MΩ		
	40MΩ	±(0.8%±2d)	*	*			
Temperature	760°C/1400°F	±(3.0%±3d)			*	*	*
Duty Cycle	0.1%~99.9%	±(1.2%±2d)		*	*	*	*
Frequency	9.999MHz	±(1.5%±4d)			*	*	*
Capacitance	200uF	±(2.5%±5d)			*	*	*
	40mF	±(2.5%±5d)					*
Diode Check	Open voltage 2.8Vdc		*	*	*	*	*
Continuity	Threshold 30Ω		*	*	*	*	*
Bat. Test	9V(6mA); 1.5V(100mA)		*				

991 Series:

Size(HxWxD): 121.5mm x 60.6mm x 40mm

Weight: 150g

Accessories: Test leads, Holster and 9V battery, clamshell.

200 Series:

Size(HxWxD): 146mm x 66.2mm x 41.5mm

Weight: 200g

Accessories: Test leads, K-type temperature probe (201, 202, 202T, 204, 204T) and 9V battery, gift box.



Model 9932FC



EMC & LVD

EN: 61326

EN: 61010-1

EN: 61010-02-032

EN: 61010-02-033



Specifications (9932FC)

Function	Max Range	Min Resolution	Basic Accuracy
Voltage DC	1000V	0.1mV	±(1.2%+2d)
Voltage AC	750V	0.1mV	±(0.8%+3d)
Current DC	20A	0.1uA	±(1.5%+3d)
Current AC	20A	0.1uA	±(1.8%+5d)
Resistance	40MΩ	0.1Ω	±(1.0%+2d)
Capacitance	100uF	10pF	±(3.5%+5d)
Frequency	9.999MHz	0.001Hz	±(1.2%+3d)
Duty Cycle	99.9%	0.1%	±(1.2%+2d)
Temperature	1000°C/1832°F	0.1°C/°F	±(3%+2°C/°F)
Diode Check	1.5VDC test 0.3mA current		
Continuity Check	Threshold 30Ω, continuity beeper 2.7kHz		



Size(HxWxD): 197mm x 88.4mm x 41.2mm

Weight: 635g

Accessories: Rubber holster, Test leads, K-type temperature probe, 9V battery, RS-232 PC cable and Software diskette, Gift box with carrying case.



По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: mce@nt-rt.ru || сайт: <https://cem.nt-rt.ru/>