

Компактные мультиметры серий DT-920, DT-921, DT-922, DT-931, DT-932, DT-918, DT-919, DT-930

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: mce@nt-rt.ru || сайт: <https://cem.nt-rt.ru/>

DT-920/920N/920L/921/921N/922/920H/922H/931H/932H

Compact True RMS Digital Multimeters

CEM



- Double molded plastic housing
- Built-in Non-Contact AC Voltage Detector (920N/921N/920H/931H/932H)

Features

	920/920N/920L	921/921N	920H	922	922H	931H	932H
Digital display counts	2000	2000	2000	4000	4000	6000	6000
True RMS measurements					*	*	*
Backlight	920L					*	*
Data Hold/REL measurements	Hold	Hold		Hold	*	Hold	Hold
LoZ low impedance measurement							*
Auto Power Off				*	*	*	*
Fast and accurate capacitance measurement					*	*	*
Auto Ranging		*		*	*	*	*
MAX/MIN Hold		MAX				*	*
Duty Cycle					*		*
Non-Contact ACV detection (NCV)	920N	921N	*			*	*
Motor shaking & LED indicator for NCV detection						*	
61-segments analog bargraph						*	*
Test 1.5V and 9V batteries			*				
Full ranges protection			*		*	*	*


Specifications

Function	Max Range	Basic Accuracy	920/920N/920L	921/N	920H	922	922H	931H	932H
Voltage DC	600V	±0.5%	*	*	*	*	*	1000V	1000V
Voltage AC	600V	±1.2%	*	*	*	*	*	1000V	1000V
Current DC	10A	±2.5%	*	*	*	*	*	*	*
Current AC	10A	±3.0%		*		*	*	*	*
Resistance	2MΩ	±0.8%	*	20MΩ	*				
	40MΩ	±0.8%				*	*		
	60MΩ	±2.0%						*	*
Capacitance	99.99mF	±3.0%				100μF	4mF	*	*
Frequency	10MHz	±1.5%				*	9.999MHz	*	*
Temperature	760°C/1400°F	±1.5%		921N		*	*	*	*
Duty Cycle	99.9%	±1.2%				*	*		*
Diode Check			*	*	*	*	*	*	*
Continuity Test			*	*	*	*	*	*	*

Size(HxWxD): 150mm x 70mm x 48mm

Weight: 255g

Accessories: Test leads, 9V battery, type K temperature probe (921/921N/922/922H/931H/932H) and gift box with carrying case.



Motor shaking &
LED indicator for
NCV detection



Model 931H



Model 932H



Model 920H



Model 922H

DT918/919



Features	DT-918	DT-919
Digital display counts	6000	6000
Safety design	*	*
Auto Ranging & Data Hold	*	*
Auto Power Off	*	*
MAX Hold	MAX/MIN	MAX/MIN
Non-Contact ACV detection		
Analog bargraph/segments	61-segments	
Display backlight	*	*
Data Hold		*
Automatic DCV or ACV selection, Capacitance, Resistance, Continuity and diode selection (919 only)		

Specifications				
Function	Max. Range	Accuracy	DT-918	DT-919
Voltage DC	600V	±0.5%	*	*
Voltage AC	600V	±1.2%	*	*
Current DC	10A	±2.5%	*	*
Current AC	10A	±3.0%	*	*
Resistance	2MΩ/20MΩ /40 MΩ	±0.8%	40 MΩ	40 MΩ
Capacitance	100μF	±3.0%	1000μF	40mF
Frequency	10MHz	±1.5%	*	*
Temperature	760°C / 1400°F	±3.0%	*	
Duty Cycle	99.90%	±1.2%	*	*
Diode Check			*	*
Continuity			*	*

DT-930/931/932/931N/932N



6000 Counts Compact Digital Multimeters

DT-930/931/932/931N/932N Series are compact meters with double molded plastic housing and over sized high contrast 6000 counts LCD display. They're all CAT III rated for 600V.

Safety Conformance

EN61010-1 CATIII 600V, CATII 1000V

Double molded plastic housing

Full ranges protection

Features	DT-930	DT-931/931N	DT-932/932N
Digital display counts	6000	6000	6000
True RMS measurements			*
Analog bargraph/segments	61-segments	61-segments	61-segments
Safety design	*	*	*
Data Hold	*	*	*
MAX/MIN recording mode	*	*	*
Auto Ranging & Auto Power Off	*	*	*
Non-Contact ACV detection		931N	932N

Specification					
Function	Max. Range	Accuracy	DT-930	DT-931/931N	DT-932/932N
Voltage DC	1000V	±0.5%	*	*	*
Voltage AC	1000V	±0.8%	*	*	*
Current DC	10A	±1.2%	*	*	*
Current AC	10A	±1.8%	*	*	*
Resistance	60 MΩ	±0.8%	*	*	*
Capacitance	1000μF	±3.0%	*	*	*
Frequency	10MHz	±1.5%	*	*	*
Temperature	760°C / 1400°F	±3.0%		*	*
Duty Cycle	99.90%	±1.2%	*	*	*
Diode and Continuity			*	*	*



По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: mce@nt-rt.ru || сайт: <https://cem.nt-rt.ru/>